

Bill of Materials PCB Shield NCS312-8 v1.0 09.11.2022 (GRA)

	#	Designator	Qty.	Value	Package	Comment
1 - Resistors	1	R63	1	18.2k	0805	Resistor
	2	R62	1	95.3k	0805	Resistor
	3	R61	1	0.1 Ohm	2512	Resistor
	4	R58	1	10k	3296W or 3266	Variable Resistor
	5	R41, R42, R56, R67	4	4.7k	0805	Resistor
	6	R55	4	10K Opt	0805	Resistor if use other U7
	7	R51	1	1 Ohm	1206	Resistor
	8	R50	1	1.5 MOhm	0805	Resistor
	9	R37, R38, R48, R54	4	1k	0805	Resistor
	10	R11, R12, R13, R14, R15, R16, R19, R20, R21, R22, R23, R24, R27, R28, R29, R30, R31, R32, R33, R34, R35, R39, R40, R43, R65	25	150 Ohm	0805	Resistor
	11	R1, R2, R3, R4, R17, R18, R36	7	150k	0805	Resistor
	12	R5, R6, R7, R8, R9, R10, R25, R26	8	27k	0805	Resistor
	13	R5222	1	0	0805	Install if used HV5222PJ
	14	R44	1	51	0805	
2 - Capacitors	15	C14	1	10nF 50V	0805	Capacitor Ceramic
	16	C12, C13, C19, C20	4	10uF 16V	0805	Capacitor Ceramic
	17	C1, C2, C3, C4, C5, C6, C8, C9, C10, C21, C22, C23	12	100nF 50V	0805	Capacitor Ceramic
	18	C7	1	10uF/ or 4.7uF 16V	Size-A (SMD3216)	Capacitor Tantalum
	19	C18	1	100nF 250V	1206	Capacitor Ceramic
	20	C11, C16	2	220uF 16V	SMD 6.3x7.7mm	Capacitor Aluminium NACE221M16V6.3X8TR13F
3 - Diodes	21	C15	1	10uF 250V (UUX2E100MNL1GS)	TH & SMD D10 x H10.5mm	Capacitor Aluminium NACV100M250V10X10.8TR13F
	22	D15	1	SS16/SS26	SMA/SMB	Schottky Diode
	23	D14	1	SMBJ220CA	SMB	TVS Diode
	24	D12	1	LED Pow RED	1206	Indicator Power LED Diode
	25	D10	4	1N4148 Opt	SOD-80C	Diode, if use other U7
26	D9	1	ES2J/ES2F	SMB	Fast Diode	
4 - IC's & Transistors	27	U1, U2, U8	3	HV5122PJ/ HV5222PG	PLCC-44	HV Driver, if used HV5122PJ - NON install R5222, if used HV5222PJ - INSTALL R5222
	28	U3	1	CD4504BM	SOIC-16	Voltage Level Translation
	29	U4	1	ULN2003D	SOIC-16	Darlington Transistor
	30	U5	1	DS3231S/ DS3231MZ	SOIC-16W/ SOIC-8	RTC
	31	U6	1	LM3478/88MM LM3478MA/MAX	MSOP-8 / SOIC-8	Step-Up HV DC-DC. Already soldered on PCB if MSOP-8.
	32	U7	1	RT8258GE	SOT23-6	Step-Down DC-DC (or Opt see schem: LMR12010/07, MCP16301)
	33	for connect TEM1 via Wire PH2.0-3p	1	DS18B20	TO-92	Temperature sensor
	34	IR1	1	TSOP4836	DIP-3	IR Receiver 36kHz
	35	Q1	1	FDD6N25/FDD6N20	DPAK	Power MOSFET
5 - Coils	36	L2	1	22uH 2A/2.6A	SMD 10.8x10.8mm	Shielded inductance
	37	L1	1	220uH 1.2A/1.5A	SMD 12x12mm	Shielded inductance
6 - Misc	38	GPS1-1, TEMP	2	Jack 3.5mm	ST-11M-030-00-0	Stereo Jack 3.5mm
	39	DOWN, MODE, UP	3	SWT-3/13	SWT-3/13, h=13, L=9	Tact button switch
	40	BT1	1	Battery Holder CR1220	SMD	Socket for BR1220,CR1220
	41	insert into the battery holder BT1	1	Battery CR1220		Battery 3V Lithium
	42	B1	1	HCS0903G	SMD 8.5x8.5mm	Buzzer
	43	DG3	1	PLS-3	Pich 2.54mm	Connect to Arduino
	44	PWR1	1	PLS-3	Pich 2.54mm	Connect to Arduino
	45	DG2, AN1	2	PLS-6	Pich 2.54mm	Connect to Arduino
	46	DG1	1	PLS-10	Pich 2.54mm	Connect to Arduino
	47	SPI1	1	PLD-4	Pich 2.54mm	Connect to Arduino
	48	ExDOWN, ExMODE, ExUP	3	PH2.0-2p	Header Pitch 2mm	For external button, LS1 for Light sensor)
49	TEM1	1	PH2.0-3p	Header Pitch 2mm	For external TEMP DS18B20	
50	for connect DS18B20 to TEM1	1	Wire PH2.0-3p	L = 10-30cm	Wire for DS18B20	
7 - RGB LED	51	D1, D2, D3, D4, D5, D6, D7, D8	8	KT-SMD3528-RGB	3528 (PLCC-4)	RGB LED Diode
8 - Nixie Tubes	52	NX1, NX2, NX3, NX4, NX5, NX6, NX7, NX8	8	IN-12A/B	RSH31a, You can solder the tubes directly to the board, or use the socket pins.	Options: Nixie Tube IN-12A/B

	53	sockets for NX1, NX2, NX3, NX4, NX5, NX6, NX7, NX8	96	Socket pin	Socket pin	Options: Sockets pin for IN-12
9 - Neon lamps	54	DS1, DS2, DS3, DS4, DS5, DS6	6	NE-2H(C2A)	Neon Lamp	Neon Lamp
10 - Mechanical	55	Hex Spacer M3 5mm	4		IN-OUT	
	56	Hex Spacer M3 12mm	4		IN-IN	
	57	Hex Spacer M3 18mm	4		IN-IN	
	58	Screw M3 L=6 mm	8			
	59	<i>for DS18B20 and Neon Lamp</i>	1	Heat Shrink 1/0.5mm	12cm	For insulation DS18B20 and Neon Lamp
	60	<i>for DS18B20 and Neon Lamp</i>	1	Heat Shrink 5/2.5mm	1.5cm	For insulation DS18B20 and Neon Lamp
	61	PCB MCU NCS312-8 v1.0	1			PCB 53.26x237mm